

JX-8P



Section	Controller	Parameter	Destination or operation when used with the [SHIFT] button
LFO	1 Pitch	Select PITCH-LFO	
	2 FILTER	Select FILTER-LFO	
	3 TYPE	LFO WAVEFORM	JX8P: LFO WAVEFORM
	4 RATE	LFO RATE	JX8P: LFO RATE
	5 FADE TIME	LFO DELAY TIME	JX8P: LFO DELAY TIME
	6 DEPTH	If "PITCH-LFO" is selected OSC1 LFO MOD OSC2 LFO MOD If "OSC 2" is selected OSC2 LFO MOD If "FILTER-LFO" is selected FILTER MOD	JX8P: OSC1 LFO MOD JX8P: OSC2 LFO MOD JX8P: FILTER MOD
OSC	7 OSC1 SEL	Select OSC1 (*1)	
	8 OSC2 SEL	Select OSC2 (*1)	
	9 SYNC	SYNC MOD MODE ON/OFF	JX8P: OSC2 MOD MODE
	10 XMOD	XMOD MOD MODE ON/OFF	JX8P: OSC2 MOD MODE
	11 TYPE	If "OSC1" is selected OSC1 WAVEFORM	JX8P: OSC1 WAVEFORM
		If "OSC2" is selected OSC2 WAVEFORM	JX8P: OSC2 WAVEFORM
	12 Pitch	If "OSC1" is selected OSC1 TUNE	JX8P: OSC1 TUNE
		If "OSC2" is selected OSC2 TUNE	JX8P: OSC2 TUNE
	13 LEVEL	If "OSC1" is selected OSC1 LEVEL	JX8P: OSC1 LEVEL
		If "OSC2" is selected OSC2 LEVEL	JX8P: OSC2 LEVEL
14 MOD	OSC2 FINE TUNE	JX8P: OSC2 FINE TUNE	
FILTER	15 [R]	Change FILTER TYPE	JX8P: VINTAGE FLT TYPE
	16 [M]	Change FILTER TYPE	JX8P: VINTAGE FLT TYPE
	17 [S]	Change FILTER TYPE	JX8P: VINTAGE FLT TYPE
	18 CUTOFF	CUTOFF	JX8P: CUTOFF
	19 RESONANCE	RESONANCE	JX8P: RESONANCE
20 KEY FOLLOW	FLT KEY FOLLOW	JX8P: FLT KEY FOLLOW	
AMP	21 LEVEL	AMP LEVEL	JP8: AMP LEVEL

Section	Controller	Parameter	Destination or operation when used with the [SHIFT] button
ENV	22 Pitch	The "TONE EDIT > OSC ENV MODE" parameter is "ENV1."	Select ENV1 Change ENV1 to OSC ENV
		The "TONE EDIT > OSC ENV MODE" parameter is "ENV2."	Select ENV2 Change ENV2 to OSC ENV
	23 FILTER	The "TONE EDIT > FILTER ENV MODE" parameter is "ENV1."	Select ENV1 Change ENV1 to FILTER ENV
		The "TONE EDIT > FILTER ENV MODE" parameter is "ENV2."	Select ENV2 Change ENV2 to FILTER ENV
	24 AMP	Select ENV-2 Change ENV-2 to AMP ENV	
	25 A	ENV1/2 ATTACK	JX8P: ENV1/2 ATTACK
	26 D	ENV1/2 DECAY	JX8P: ENV1/2 DECAY
	27 S	ENV1/2 SUSTAIN	JX8P: ENV1/2 SUSTAIN
	28 R	ENV1/2 RELEASE	JX8P: ENV1/2 RELEASE
	29 DEPTH	If "PITCH ENV" is selected If "OSC 1" is selected OSC1 PIT ENV	JX8P: OSC1 PIT ENV
If "OSC 2" is selected OSC2 PIT ENV		JX8P: OSC2 PIT ENV	
EDIT	30 MONO	If "FILTER ENV" is selected FLT ENV DEPTH	JX8P: FLT ENV DEPTH
		If "AMP ENV" is selected Not operable	
	31 UNISON	UNISON	JX8P: KEY MODE
	32 PORTAMENTO	PORTAMENTO	JX8P: PORTA TIME
	33 SPLIT	SPLIT	
	34 DUAL	DUAL	L/R DUAL

* 1 Valid only in function mode.
* For other parameters, refer to "Parameter Guide" (PDF).